


□□□ , 2□□□ -2□□□ , 1,000 A IEC, □
 , □□□□

Data Solutions

???

SB2C2C1000AL



nVent ERIFLEX

????????????????????(???????)??/?????? DIN

????/?????????????????????????????????

????????????????????4????nVent ERIFLEX Flexibar Advanced,
 ??IBSB Advanced ?????

??



??

???????????????? nVent ERIFLEX Flexibar Advanced ? IBSB Advanced ??????

????????????????

????????????????????????????

????????????

????????????????

????????????????

????? DIN ?????????

????????

??? 95%

????????????????????(RoHS) ??

?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?

????????? ??????

???: 561175
?: ??
?: 2 ??? - 2 ???
????????IEC: 1000A
?: ?; ???
????????IEC: (2) 300 mm²
????????IEC: (2) 300 mm²
????? (ICW) 1 ? : 72kA
???????IEC: 1150A
???????UL/CSA: 840A
????? (Ipk): 75kA
??????? (ICC): 35.7kA
????? (SCCR): 100kA
???????IEC (Ui): 1000; 1500
???????UL (Vin): 1000
??????? : 2
??????????? : #2 - 600 kcmil; 35-300 mm²
??? DLO ??? : #2 - 373 kcmil
??????????? : (2) 35 - 300 mm²
??? DLO ??? : #2 - 373 kcmil
??????? : 2
????????? - ? : (2) 35 - 300 mm²
??????? : (2) #2 - 600 ???
?? (D): 110mm
?? (H): 223mm
?? (W): 44mm
????: 0.72kg
?????: UL® 1953
?: IEC® 60947-7-1
?????: IP 20
?????: UL® 94V-0

SBF250?SB250SPCR?????UL1953????? ??UL® 1953?????????1250VAC/DC?

XXXXXXXXXXXX										
????*?? (°C) ????? 85°C ?????										
???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47
*?????????????										



???? nVent ?????????????????? nVent ???????? www.nvent.com ?????????????? nVent ?? nVent
??



?????????????:
CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE