


SBTT-500

Data Solutions

???

SBTT-500



??



??

???????????????

???????????????

???????????????????

???????????

???????

???????????????????

????? DIN ??????????????

????????? SBLEC ??????????

????????????????????????????????(RoHS) ??

???

????

???: 561145

?: ?; ??

?: ??


???????IEC: 750A
???????UL/CSA: 500A
?????? (ICW) 1 ??: 28.8kA
?????? (Ipk): 52kA
?????? (SCCR): 100kA
???????IEC (Ui): 1000; 1500
???????UL (Vin): 1000
?????: 4
?????????????: (4) 16 – 120 mm ²
???????? - ??: (4) 16 – 120 mm ²
????????: (4) #6 – 250 kcmil
?? (D): 66mm
?? (H): 205.7mm
?? (W): 85.1mm
A: 108mm
????: 0.6kg
?????: UL® 1059
?????: UL® 94V-1
?: IEC® 60947-7-1

??????

????????????????????????

????*?? (°C) ????? 85°C ?????										
???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47
*???????????										

?



??

???? nVent ?????????????????? nVent ??????? www.nvent.com ?????????? nVent ?????????????????????????????? nVent
??



?????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE