



, 250 A IEC, 255 A UL/CSA,
Line, 6  Load,  ,



Data Solutions

???

UDF-250A



??



??

????????????????????????????

????????????

????????????????

????????????????

????? DIN ?????????????

??? 95%

????????????????????????????(RoHS) ??

?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?

???

??????????

???: 569041

???????IEC: 250A

???????UL/CSA: 255A

?????: ???

?????: 6 ???

??: ?; ???

????????IEC: 70 mm²

????????IEC: 16 mm²

???????IEC (Ui): 1000

???????UL (Vin): 600

?????? (ICW) 1 ? : 9kA

?????? (I_{pk}): 23kA

???????? (ICC): 11.5kA

?????? (SCCR): 100kA

??????: 1

??????: 6

?????????: (6) 2,5 - 16 mm²

???????? - ??: (6) 2,5 - 16 mm²

??????: (6) #14 - #4

??????: IP 20

?? (D): 46mm

?? (H): 79mm

?? (W): 29mm

????: 0.15kg

?????: UL® 1059

?????: UL® 94V-0

?: IEC® 60947-7-1

160A IEC




UL ?????????1000V AC/DC????????????

1111111111111111

????*?? (°C) ????? 85°C ?????

???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47

*??????????



???? nVent ?????????????????? nVent ??????? www.nvent.com ???????????? nVent ??? nVent
??/??????????????



?????????:
CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE