

DT 11111 , 240 kA, 111 , 230/400 V, 3Ph+N TT 11

Data Solutions

???

DTX240F400TT



nVent ERICO DTX240 (SPD)
 IEC I II UL 1 2
 B DTX240
 240 kA C
 (MCC) (HVAC) nVent ERICO DTX240
 NEMA®-4X

??

(UL)

SPD

RS-485

?? 53 dB ??10 kHz ? 100 MHz?? F ??

10

????

(Un): 230/400 V

3 ? 4W+G

(Uc): 300/520 VAC

(In)?IEC: 40kA 8/20 ?s

(In)?IEC?N-PE: 100kA 8/20 ?s

(Imax)?N-PE: 240kA 8/20 ?s

(Imax)?: 240kA 8/20 ?s

(Iimp)?: 17.5kA 10/350 ?s

(Iimp)?N-PE: 70kA 10/350 ?s

?: -29 dB @ 100 kHzdB

?: 50 – 60Hz

????: L-N; L-PE; N-PE

?: 40 to 80°C

?: ? Hoffman ???

????: ?

?????: NEMA®-4X; UL® 50E 4 ?; IP66

????: 2 – 13mm²

?????: 2.0 A @ 240 V

????: ?C ?

????? (Isc): 50kA

????: ??????????; ???? LED?????????; ????; OLED ???; ????; ??/TOV ???????

?: ???????????

????? (Up)?IEC: 1200 V @ 20 kA; 3000 V @ 100 kA

?: EN 61643-11 1 ?? ?; IEC® 61643-1 I ??II ?; ANSI®/IEEE® C62.41.2-2002 A ??B ??C ?; ANSI®/IEEE® C62.41.1-2002 A ??B ??C ?

?? (D): 140.2mm


?? (H): 355.1mm

????: 9.75kg

?? (W): 329.9mm

????: DT1300M; SGT1100M

?



??

???? nVent ?????????????? nVent ?????? www.nvent.com ?????????? nVent ?????????????????????????? nVent
??



?????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE