

□□□ , □□ -□□ , 170 A IEC, □ , □□□□□

Data Solutions

???

SB125



nVent ERIFLEX
????????????????????(???????)??/?????? DIN
?????/??
????????????????????4????nVent ERIFLEX Flexibar Advanced,
??IBSB Advanced ?????

??



??

- ???????????????? nVent ERIFLEX Flexibar Advanced ? IBSB Advanced ??????
- ?????????????????
- ??
- ???????????????
- ???????????????????????
- ???????????????????????
- ????? DIN ????????????????
- ???????????????
- ?? 95%
- ????????????????????????????(RoHS) ??
- ?? EN 45545???? R23 ?? HL3 ?? R22 ?? HL2 ?
- ???????????? ???????

????

???: 561158

?: ??

?: ??-??

????????IEC: 170A

?: ?; ???

????????IEC: 35 mm²

????????IEC: 35 mm²

????? (ICW) 1 ?: 6kA

????????IEC: 170A

????????UL: 150A

????? (Ipk): 25kA

???????? (ICC): 12.5kA

????? (SCCR): 100kA

????????IEC (Ui): 1000; 1500

????????UL (Vin): 1250

????????: 1

?????????: 10-35 mm²; #8 - 1/0

?????????: 10-35 mm²; #8 - 1/0

????????: 1

???????? - ??: 10-35 mm²

?? (D): 46.9mm

?? (H): 84mm

?? (W): 20.2mm

????: 0.07kg

?????: UL® 1059

?: IEC® 60947-7-1

?????: IP 20

?????: UL® 94V-0

??????

SBF250?SB250SPCR?????UL1953????? ??UL® 1953????????1250VAC/DC?

????????????????????7%

□□□□□□□□□□										
????*?? (°C) ????? 85°C ?????										
???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47
*???????????										

?



??

??? nVent ?????????????????? nVent ?????? www.nvent.com ?????????????? nVent ?????????????????????????????????????? nVent
 ???



?????????:
 CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE