

□□□ , □□ -□□ , 400 A IEC, □ ,
□□□□□

Data Solutions

???

SB250AL



nVent ERIFLEX

????????????????????(???????)??/?????? DIN
????/?????????????????????????????????

????????????????????4????nVent ERIFLEX Flexibar Advanced,
??IBSB Advanced ?????

??



??

??????????????? nVent ERIFLEX Flexibar Advanced ? IBSB Advanced ?????

????????????????

????????????????????????????

????????????

????????????????

????????????????

????? DIN ?????????

????????

??? 95%

????????????????????(RoHS) ??

?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?

????????? ??????

???: 561163

??: ??-??

????????IEC: 400A

??: ?; ???

????????IEC: 120 mm²

????????IEC: 120 mm²

?????? (ICW) 1 ? : 14.4kA

??????IEC: 400A

???????UL/CSA: 255A

????? (I_{pk}): 42kA

???????? (ICC): 20kA

?????? (SCCR): 100kA

???????IEC (Ui): 1000; 1500

???????UL (Vin): 1250

??????: 1

?????????: 35 - 120 mm²; #6 - 250 ????

??????????: 35 - 120 mm²; #6 - 250 ????

??????: 1

???????? - ??: 35 - 120 mm²

?? (D): 58mm

?? (H): 111mm

?? (W): 31.5mm

????: 0.13kg

?????: UL® 1059

?: IEC® 60947-7-1

??????: IP 20

?????: UL® 94V-0

SBF250?SB250SPCR?????UL1953????? ??UL® 1953??????????1250VAC/DC?

????????????????7%

[illegible]

????*?? (°C) ????? 85°C ?????

???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47

*??????????



???? nVent ?????????????? nVent ??????? www.nvent.com ?????????? nVent ?????????????????????????????????????? nVent
??/?????????????



?????????:
CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE