

□□□ , □□ -□□ , 630 A IEC, □ , □□□□□

Data Solutions

???

SB630



nVent ERIFLEX
????????????????????(???????)??/?????? DIN
?????/????????????????????????????????????
????????????????????4????nVent ERIFLEX Flexibar Advanced,
??IBSB Advanced ?????

??



??

???????????????? nVent ERIFLEX Flexibar Advanced ? IBSB Advanced ??????
?????????????????
????????????????????????????????????
?????????????
????????????????????
????????????????????
????? DIN ??????????????
????????????
??? 95%
????????????????????????????(RoHS) ??
?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?
???????????? ???????

????

???: 561156

?: ??

?: ??-??

????????IEC: 630A

?: ?; ???

????????IEC: 500 mm²

????????IEC: 500 mm²

????? (ICW) 1 ?: 60kA

????????IEC: 870A

????????UL: 545A

????? (Ipk): 51kA

???????? (ICC): 24.3kA

????? (SCCR): 100kA

????????IEC (Ui): 1000; 1500

????????UL (Vin): 1250

????????: 1

?????????: 240 - 500 mm²; 400 - 1,000 kcmil

?????????: 240 - 500 mm²; 400 - 1,000 kcmil

????????: 1

???????? - ??: 240 - 500 mm²

?? (D): 89.4mm

?? (H): 174.4mm

?? (W): 54.2mm

????: 1.2kg

?????: UL® 1059

?: IEC® 60947-7-1

?????: IP 20

?????: UL® 94V-0

??????

SBF250?SB250SPCR?????UL1953????? ??UL® 1953????????1250VAC/DC?

????????????????????7%

□□□□□□□□□□										
????*?? (°C) ????? 85°C ?????										
???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47
*???????????										

?



??

??? nVent ?????????????? nVent ?????? www.nvent.com ?????????? nVent ?????????????????????????????????? nVent
 ???/?????????????



?????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE