

□□□ , □□ -□□ , 100 A IEC, □ ,
□□□□□

Data Solutions

???

SB80AL



nVent ERIFLEX
 ??????????????????????(???????)???/??????? DIN
 ?????/????????????????????????????????????
 ?????????????????????4????nVent ERIFLEX Flexibar Advanced,
 ??IBSB Advanced ?????

??



??

??????????????? nVent ERIFLEX Flexibar Advanced ? IBSB Advanced ??????

????????????????

????????????????????????????

????????????

????????????????

????????????????

????? DIN ?????????

????????

??? 95%

????????????????????????(RoHS) ??

?? EN 45545???? R23 ?? HL3 ??? R22 ?? HL2 ?

????????? ??????

???: 561160

??: ??

??: ??-??

????????IEC: 100A

??: ?; ???

????????IEC: 16 mm²

????????IEC: 16 mm²

?????? (ICW) 1 ? : 3kA

??????IEC: 105A

??????UL/CSA: 85A

?????? (I_{pk}): 22kA

???????? (ICC): 11kA

?????? (SCCR): 100kA

??????IEC (Ui): 1000; 1500

???????UL (Vin): 1000

??????: 1

?????????: 6-16 mm²; #16 - #4

??????: 2.5 - 6 mm²; #16 - #10

?????????: 6-16 mm²; #16 - #4

??????: 1

?????????: 2.5 - 6 mm²; #16 - #10

???????? - ??: 6-16 mm²

?? (D): 42mm

?? (H): 84mm

?? (W): 17.3mm

????: 0.04kg

?????: UL® 1059

?: IEC® 60947-7-1

?????: IP 20

?????: UL® 94V-0

SBF250?SB250SPCR?????UL1953????? ??UL® 1953??????????1250VAC/DC?

????????????????7%

1000000000000000000

????*?? (°C) ????? 85°C ?????

???? (°C)	30°	35°	40°	45°	50°	55°	60°	65°	70°	75°
???? (d)	1	1	1	0.94	0.88	0.82	0.75	0.67	0.58	0.47

*??????????



???? nVent ?????????????? nVent ??????? www.nvent.com ?????????? nVent ?????????????????????????????????????? nVent
??/????????????



?????????:
CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE