


SBLT-250

Data Solutions

???

SBLT-250



??



??

???????????????

?????????????? nVent ERIFLEX Flexibar ????????

?????????????????????

???????

?????????????????????

????? DIN ????????????????

????????? SBLEC ??????????

????????????????????????????????(RoHS) ??

???

?????

???: 561140

??: ?; ???

??: ??

????????IEC: 350A

??????UL/CSA: 300A

????? (ICW) 1 ? : 8.4kA

????? (Ipk): 30kA

????? (SCCR): 100kA

??????IEC (Ui): 1000; 1500

??????UL (Vin): 1000

?????: 1

??????: 20 – 24 mm

?????????: 10 – 120 mm²

??????: #6 - 250 ????

?????: 2

?????????: (2) 10 – 50 mm²

?????? - ??: (2) 10 – 35 mm²

????????: (2) #8 – 1/0

?? (D): 65mm

?? (H): 205.7mm

?? (W): 52.3mm

A: 108mm

????: 0.27kg

?????: UL® 1059

?????: UL® 94V-1




?: IEC® 60947-7-1

??????

????????????????????

| ????*?? (°C) ????? 85°C ????? | 30° | 35° | 40° | 45° | 50° | 55° | 60° | 65° | 70° | 75° |
|-------------------------------|-----|-----|-----|------|------|------|------|------|------|------|
| ???? (d) | 1 | 1 | 1 | 0.94 | 0.88 | 0.82 | 0.75 | 0.67 | 0.58 | 0.47 |
| *???????? | | | | | | | | | | |

?



??

??? nVent ?????????????? nVent ?????? www.nvent.com ?????????? nVent ?????????????????????????????????????? nVent
??/?????????????



??????????:

CADDY ERICO HOFFMAN ILSCO SCHROFF TRACHTE